

# Isotron<sup>®</sup> accelerometer Model 65HTLPF





## Key features

- Triaxial, low-impedance out put with 2-pole low pass filter
- Rated for continuous use up to +175°C (347°F)
- Small size (10-mm cube, 5 gram)
- 65HTLPF-10-02-R and 65HTLPF-10-10-R available as replacement sensors

## Description

The Endevco® model 65HTLPF is a miniature IEPE high temperature (up to 175°C) triaxial accelerometer with 2-pole low-pass filter. The sensor is designed for use in test and measurement applications requiring both high temperature operation and effective attenuation of high-frequency, high-g signals that can obscure the required low-frequency information and also can cause saturation of electronics. Additionally, the low-pass filter provides resonance suppression. The model 65HTLPF is packaged in a 10 mm cube of welded titanium construction. Interface to the model 65HTLPF triaxial accelerometer is made via a side connector Microtech style 4-pin receptacle. Power to the sensor, in the form of a constant current, travels through the same pins as the low impedance output signals.

The model 65HTLPF-10 features a sensitivity of 10 mV/g. The model number's second suffix indicates the low-pass filter corner frequency at level – 3dB. Two options are currently available, the model 65HTLPF-10-02 featuring a corner frequency of 2 kHz and the 65HTLPF-10-10 featuring a corner frequency of 10 kHz. Other corner frequencies are available upon request.

This product is fully compliant to the European Union's Low Voltage Directive, 2006/95/EC and EMC Directive 2004/108/EC and is eligible to bear the CE Mark.





# Isotron<sup>®</sup> accelerometer | Model 65HTLPF

The following performance specifications conform to ISA-RP-37.2 (1964) and are typical values, referenced at +75°F (+24°C) and 100 Hz, unless otherwise noted. Calibration data, traceable to National Institute of Standards and Technology (NIST), is supplied.

Specifications				
Dynamic characteristics	Units	-10-02		-10-10
Range	g		±500	
Voltage sensitivity				
Typical	mV/g		10	
Tolerance	%		10	
Frequency response			See typical amplitude response	
Amplitude response		E . 4000		E
±5%	Hz	5 to 1000		5 to 5000
±1 dB	Hz	3 to 1400	40.000	3 to 7000
Resonance frequency	Hz	0.00	40 000	10 . 1
Low-pass filter corner frequency (-3 dB)	kHz	2 ±0.2	10.10 5	10 ±1
Low-pass filer roll-off	dB/Octave		10-12.5 See turning annua	
Temperature response		De statione a la	See typical curve	- f 77%E (2E%C)]
Sensitivity deviation Sensitivity deviation			solute value <15% at -67°F (-55°C) [re bsolute value <30% at +347°F (+175	
Transverse sensitivity	%	negative a	< 5	
Amplitude linearity	%		< 1	
	/6		< 1	
Dutput characteristics				
Output polarity			See arrows on outline drawing	
DC output bias voltage [1]	Vdc	+	+9.5 to +13.5 at room temperature	
		-	+8 to +16 over temperature range	
Output connection			See connection diagram	
Output impedance			-	
1 mA to 2 mA	Ω		< 300	
3 mA to 4 mA	Ω		< 100	
Full scale output	Vpk		±5	
Saturation level at 5Vpk output				
100 Hz	gpk	500		500
1 kHz	gpk	500		500
2 kHz	gpk	≥ 700		500
5 kHz	gpk	≥ 5000		500
10 kHz	gpk	≥ 5000		≥ 700
40 kHz (resonance frequency)	gpk	≥ 350		≥ 800
Noise floor			. 1000	
Broadband (0.1 Hz to 10 kHz)	µg rms		≤ 4000	
Spectral:			< 1000	
1 Hz 10 Hz	µg / √ Hz		≤ 1000 ≤ 170	
100 Hz	µg / √ Hz	≤ 70	\$ 170	≤ 40
1 kHz	µg / √ Hz	≤ 70 ≤ 70		≤ 40 ≤ 40
Grounding	µg / √ Hz		Signal ground connected to the case	<u><u> </u></u>
-				
Power requirement				
Current requirement	mA		+1 to +4	
Voltage supply	Vdc		+23 to +30	
Warm-up time (time to reach 90% of final bia	s) sec		< 2	
Environmental characteristics				
Temperature range			-67°F to +347°F (-55°C to +175°C)	
Humidity			Welded construction	
Sinusoidal vibration limit (without damage)	g pk		±5000	
Shock limit (without damage) [2]	g pk		10 000	
Base strain sensitivity at 250µ strain	eq. g/µstrain		< 0.001	
Thermal transient sensitivity	eq. g/°F		0.02	
•	34.97.			
Physical characteristics				
Dimensions			See outline drawing	
Weight	oz (gram)		0.17 (5)	
Case material			Titanium, commercially pure Cp4	
Connector [3]			4-pin Microtech-style, side mounted	
Mounting [4]	1. II. C		Adhesive or M2.5 thread	
Mounting torque	in-lbf		8	
Calibration				
Supplied, each axis:				
Sensitivity	mV/g			
	mV/g %			
Sensitivity Transverse sensitivity Frequency response	0	20 to 2200		20 to 11000

#### Isotron<sup>®</sup> accelerometer | Model 65HTLPF

Accessories			
Options	Description	65HTLPF	65HTLPF-R
3027AM3-36	Triaxial cable 85" C, 3 BNC's at instrumentation end [6]	Included	Optional
3027AVM13-84	Extension cable, 84 inches, rated to +200°C (mates with 3027AM3) [5]	Included	Optional
3027AVM13-XXX	Extension cable rated to +200°C (mates with 3027AM3) [5]. -XXX defines cable length in inches.	Optional	Optional
32279	Mounting wax	Included	Optional
EH755	Screw cap M2.5 x .45 x 6 mm	Included	Included
EH761	Screw set M2.5 x .45 x 6 mm	Included	Included
40965	Mounting block, adhesive mount	Optional	Optional
EH769	Screw for 40965 mounting block	Optional	Optional
41013	Mounting clip	Optional	Optional
2981-14	Mounting stud, M2.5 to 6-32	Optional	Optional
2793	Isotron signal conditioner	Optional	Optional
4990A-1	OASIS 2000 computer controlled system	Optional	Optional
2981-14	Adapter stud, M2.5 to 6-32	Optional	Optional
		I	

### Notes

- 1. +22 Vdc minimum must be available to the accelerometer to ensure full-scale operation at the temperature extremes.
- 2. Shock pulses of short duration may excite sensor resonance. Shock level above the sinusoidal vibration limit may produce temporary zeroshift which will result in erroneous velocity or displacement data after integration.
- 3. Microtech DR-4S-4 receptacle mates with Endevco® model 3027AM3 and 3027AVM13 cables
- 4. Be careful not to apply excessive force when removing the accelerometer from structure. Hammer taps and wrench "snaps" often impart permanent damage to the case and internal sensors.
- 5. The 3027AVM13 cable assembly should be used where the accelerometer is used near its upper temperature extreme, 347°F (175°C).
- 6. 3027AM3 cable assembly should be used as a 185°F (85°C). extension cable for model 3027AVM13.
- 7. Case isolation available as models 65HTLPFM1-10-02 and 65HTLPFM1-10-10. For these models, signal ground is connected to the case and isolated from the mounting surface.
- Maintain high levels of precision and accuracy using Endevco's factory calibration services. Call Endevco's inside sales force at 866-ENDEVCO for recommended intervals, pricing and turn-around time for these services as well as for quotations on our standard products.



10869 NC Highway 903, Halifax, NC 27839 USA

AN AMPHENOL COMPANY

F

NDEV

endevco.com | sales@endevco.com | 866 363 3826

© 2021 PCB Piezotronics - all rights reserved. PCB Piezotronics is a wholly-owned subsidiary of Amphenol Corporation. Endevco is an assumed name of PCB Piezotronics of North Carolina, Inc., which is a wholly-owned subsidiary of PCB Piezotronics, Inc. Kecker for any third party marks for which attribution is provided herein, the company names and product names used in this document may be the registered trademarks or unregistered trademarks of PCB Piezotronics, Inc., PCB Piezotronics of North Carolina, Inc., (d/b/a Endevco), The Modal Shop, Inc. are wholly-owned subsidiary of Amphenol Corporation. Endevco is an assumed name of PCB Piezotronics, Inc. Except for any third party marks for which attribution is provided herein, the company names and product names used in this document may be the registered trademarks or unregistered trademarks of PCB Piezotronics, Inc., PCB Piezotronics of North Carolina, Inc. (d/b/a Endevco), The Modal Shop, Inc. or Accumetrics, Inc. Inc. PCB Piezotronics of North Carolina, Inc. (d/b/a Endevco), The Modal Shop, Inc. or Accumetrics, Inc.